

XP-S200N / S300N

Thermal Receipt Printer

Xprinter®

- Easy Maintenance: Takes 5S to update firmware only;
- User can search and manage Lan Printer directly by software;
- Steady performance: Resume from cutter jam error automatically;
- Excellent compatibility performance on different operating system;



Coffee Shop



Shopping




Mart



XP-S200N/S300N

Thermal Receipt Printer



Model	XP-S200N		XP-S300N
Printing method	Direct thermal		
Paper width	79.5±0.5mm		
Print width	72mm/ 76mm/ 80mm/ 64mm/ 48mm/ 52mm		
Column capacity	576 dots/line(adjustable by command)		
Printing speed	200 mm/s Max.		300 mm/s Max.
Interface	USB+Lan/USB+Serial (Optional: WIFI/Bluetooth)		USB+Serial+Lan
Line spacing	3.75mm(Adjustable by commands)		
Column number	80mm paper: Font A - 42 columns or 48 columns/Font B - 56 columns or 64 columns/ Chinese, traditional Chinese - 21 columns or 24 columns		
Character size	ANK, Font A: 1.5×3.0mm(12×24 dots) Font B: 1.1×2.1mm(9×17 dots) Chinese, traditional Chinese:3.0×3.0mm(24×24 dots)		
Cutter			
Auto cutter	Partial		
Barcode Character			
Extension character sheet	PC347(Standard Europe) / Katakana / PC850(Multilingual) / PC860(Portuguese) / PC863(Canadian-French) / PC865(Nordic) / West Europe / Greek / Hebrew / East Europe / Iran/WPC1252 / PC866(Cyrillic#2) / PC852(Latin2) / Pc858 / IranII / Latvian / Arabic / PT151(1251)		
Barcode types	UPC-A/UPC-E/JAN13(EAN13)/JAN8(EAN8)/CODE39/ITF/CODABAR/CODE93/CODE128		
2D Barcode	QR CODE / PDF417		
Input buffer	128 Kbytes		2048 Kbytes
NVFlash	256 Kbytes		
Power			
Power adaptor	Input: AC 100-240V/50~60Hz; Output: DC 24V/2.5A		
Printer input	DC 24V/2.5A		
Cash drawer	DC 24V/1A		
Physical characteristics			
Weight	1.3 Kg		
Dimensions	195×140×136mm (D×W×H)		
Environmental Requirements			
Operation environment	Temperature (0 ~ 45℃) humidity(10 ~ 80%)		
Storage environment	Temperature(-10 ~ 60℃) humidity(10 ~ 90%)		
Reliability			
Cutter life	1.5 million cuts		
Printer head life	150 KM		
Software			
Emulation	ESC/POS		
Driver	Windows/JPOS/ OPOS/Linux/Android/Mac		
Utility	Windows & Linux test Utility		
SDK	iOS/Android/Windows		



Scan QR code to checkout Xprinter website for more update information.
Phone: (+86 756) 3895 852
Http://www.xprintertech.com
Email: overseas@xprinter.net

